

American DJ **FREQ Matrix**

Add more creativity to your lightshow with ADJ's **FREQ MATRIX** revolutionary 16-Zone LED Strobe matrix. This 2-FX-IN-1 fixture features traditional LED strobe + 16-Zone matrix chase effect. The matrix zone chase effect gives lighting designers the ability to create exciting and dynamic energy-driven lighting shows.

The **FREQ MATRIX** offers full DMX control with 4 DMX channel modes, dimming, strobe speed and chase speed. Users can also run the **FREQ MATRIX** in sound active mode, or manually control strobe speed and dimming on the back of the unit from it's potentiometer knobs.

The **FREQ MATRIX** uses sixteen 5-Watt bright white LEDs and consumes a maximum of 107-watts of power.

Specifications:

- 2-FX-IN-1: Traditional LED Strobe/Blinder + 16-Zone chase effect
- 16x 5-Watt White bright LEDs (30,000 hr. rated)
- 4-Button DMX LED Display
- 3 Operational modes: DMX controller, Master/Slave & Sound Active
- 4 DMX Channel modes (1, 2, 16 or 18 Ch.)
- Strobe speed: control via DMX or potentiometer knob on rear of unit
- 0-100% dimming: control via DMX or potentiometer knob on rear of unit
- Includes exciting sound activate built-in matrix programs
- LED pulse & strobe effect
- Strobe up to 1200 times per minute
- Fan Cooled
- Extremely Long Life (30,000 hr. rated)
- Runs extremely cool! - NO Duty Cycles! – Run all night!
- Includes hanging bracket
- Safety hook on rear panel
- Very low power consumption - connect more units in a single circuit
- IEC AC IN/OUT on rear to daisy chain power (up to 3 Freq Matrix's @ 120V and 6 Freq Matrix's @ 230V)
- Compatible with American DJ UC3 Series easy-to-use controllers (sold Separately)
- Power Consumption: 107W maximum
- Multi-voltage Operation: AC 100 - 240V, 50/60Hz
- Dimensions (LxWxH): 11.75" x 11.5" x 4.75" / 295 x 291 x 115mm
- Weight: 8 lbs. / 3.6 kg.

